Rechargeable **FISHMAN** FLUENCE Battery Pack HSS Wiring with SSP, SSA, & Classic Bridge Humbucker Neck: SSP Classic Bridge +9V Middle: SSA Single Width Pickup (Red) Single Width Pickup Humbucker +3dB Boost Pads (top side of PCB) Bridge with solder Inline to activate. Connector (Recommended) FLUENC lassic Bri Bridge Ground Bridge Pickup Voice-3 Not Used 000 Output Output Jack Side Detail Jack Mag Volume Place phase jumper in position that provides the most bass response SSA Pickup - Wire Color Scheme Pickup Selector Function with both Mag & Piezo Red: +9V 1. Bridge Humbucker signals on. SSA Coil(s) Out White: 2. Bridge Coil Tapped & Middle Powerchip Top Detail 25k Yellow: Preamp In 3. Middle Preamp Out Green: Mag In 4. Neck & Middle 2&4 Position Dual Single Mode (Position 4) Blue: 5. Neck 2&4 HB Tapped + Single Mode (Position 2) Black: **GND** Shield: Mag Tone Neck Pickup Pull for SSP Pickup Output Bridge Voice-2 This is a passive pickup used in conjunction with the SSA active pickup and it's preamp. Powerchip Pickup Selector Piezo Mute Piezo Preamp 5-Position Powerbridge (Bottom View) 4P5T "Super Switch" Cable 3-way Switch On-Óff-On (Stewmac # 7465)