## Regulator/Charger Battery **FISHMAN** FLUENCE Modern Humbucker Set & Powerbridge/Powerchip 5-way Super Switch with coil taps Note: "V1 Gain" not used, Ground for Voice 1 Low Gain setting Bridge Pickup: Modern Ceramic Neck Pickup: Modern Alnico Mag Signal Neck Mag Tone Vol. Output Neck Voice-2 Тор Jack Powerchip Preamp (Bottom) Piezo Tone 25k Bridge Vol. 0 Neck Jumper O PZ IN Pull Wire Bridge Voice-2 Out to Tone #2 \* Note: Piezo Tone control leverages an existing capacitor on the Powerchip Output Jack Side Detail Pickup Selector, Bridge input. 5-Way Super-Switch Mag ON Lever Positions Oak Grigsby OFF (Stewmac # 3200) Powerchip Top Detail Powerbridge 3-way Switch On-Off-On Piezo Output Postitions: Mag In 1. Bridge \* Note: Control cavity (Stewmac # 7465) 2. B&N - Tapped - Outer Coils Bridge must be 100% shielded 3. B&N Ground to prevent noise on 4. B&N - Tapped - Inner Coils the piezo signal. 5. Neck Output Piezo Mute